

## Signal Level Meter

HT-828B /T1125

HT-828B is an analog Television signal Level Meter, it enables showing C/N, Trunk Voltage, and V/A on Full size LED displayer, and it can simultaneously measure two channels.



### Frequency and level

Frequency range	46-870MHz /5-860MHz
Resolution bandwidth	280KHz+/-50KHz
Channels	All user Channels
Level range:	30-115dBuV
Accuracy	+/-1.5dBuV
Input impedance	75ohm
Interface	Male-F connector or BNC
Wave detection	Peak value

### Voltage

Voltage range	0-100VAC
Accuracy	+/-1.5V
Resolution	0.1V
C/N	
Level Range	80dBuV-105dBuV

### General

Dimension	215x95x47mm
Weight:	550g
Working temperature	-10+40
LCD	STN LCD
DC supply	DC 7.2/1.6Ah rechargeable battery
AC supply	USA or Euro